

HIOKI · CLAMPMETERS · DATASHEET

Hioki CM3289 Clampmeter 1000A AC

Model CM3289



Slim-jaw 1000A AC clamp meter with True RMS measurement. $\Phi 33\text{mm}$ jaw fits crowded panels. Measures AC current to 1000A, AC/DC voltage to 600V and resistance to 42M Ω . V: CAT III 300V / A: CAT IV 300V. Coin-battery powered, drop-proof.

Price and availability

Ask Industrial Supply Syndicate for the current price, stock and a quotation with GST and freight. Call +91 89610 89611 or WhatsApp +91 89610 89611.

Key Features

- True RMS measurement for accurate readings on distorted waveforms
- AC current up to 1000A (guaranteed range 4.00A to 1000A)
- Slim $\Phi 33\text{mm}$ jaw for crowded wiring
- AC and DC voltage up to 600V
- Resistance up to 42 M Ω and continuity check
- V: CAT III 300V / A: CAT IV 300V safety rating
- Drop-proof; CR2032 coin battery, approx. 70 hours operation
- Auto power off and auto range

Compatible accessories

- Hioki 9209 Test Lead Holder (Model 9209)
- Hioki 9398 Carrying Case (Model 9398)
- Hioki CT6280 AC Flexible Current Sensor (Model CT6280)
- Hioki L4933 Contact Pin Set (Model L4933)
- Hioki L4934 Small Alligator Clip Set (Model L4934)

Order or ask for a quotation

Industrial Supply Syndicate supplies the Hioki CM3289 across India with a GST invoice. Tell us the quantity and delivery location; we reply with a quotation or proforma invoice including freight.

Phone +91 89610 89611
WhatsApp +91 89610 89611
Email info@hiokimeters.com
Online hiokimeters.com/product/cm3289-clampmeter-1000a/
Address 54, Ezra Street,, Kolkata – 700 001, West Bengal, India
GSTIN 19ACDPC1843J1ZR



Scan to WhatsApp us